

# Remarks on the Restricted Isometry Property in Orthogonal Matching Pursuit algorithm

QUN MO

YI SHEN

Research supported in part by the NSF of China under grant 10971189, the China Postdoctoral Science Foundation under grant 20100481430, the Doctoral Program Foundation of Ministry of Education of China under grant 20070335176 and Science Foundation of Chinese University under grant 2010QNA3018.

Q. Mo is with the Department of Mathematics, Zhejiang University, Hangzhou, 310027, China (e-mail: moqun@zju.edu.cn ).

Y. Shen is the corresponding author. He is with the Department of Mathematics, Zhejiang University, Hangzhou, 310027, China (e-mail: sy1133@zju.edu.cn).

*July 16, 2018*

## Abstract

This paper demonstrates theoretically that if the restricted isometry constant  $\delta_K$  of the compressed sensing matrix satisfies

$$\delta_{K+1} < \frac{1}{\sqrt{K} + 1},$$

then a greedy algorithm called Orthogonal Matching Pursuit (OMP) can recover a signal with  $K$  nonzero entries in  $K$  iterations. In contrast, matrices are also constructed with restricted isometry constant

$$\delta_{K+1} = \frac{1}{\sqrt{K}}$$

such that OMP can not recover  $K$ -sparse  $x$  in  $K$  iterations. This result shows that the conjecture given by Dai and Milenkovic is true.

**Keywords:** compressed sensing, restricted isometry property, orthogonal matching pursuit, sparse signal reconstruction.

⟨IEEEpeerreviewmaketitle⟩

## 1 Introduction

Compressive sensing is a new type of sampling theory, that predicts that sparse signals and images can be reconstructed from what was previously believed to be incomplete information [CT]. The key idea is that the sparsity helps in isolating the original vector. Let  $x \in \mathbf{R}^n$  be a signal, we want to recover it from a linear measurement

$$Ax = y, \tag{1}$$

where  $A$  is a given  $m \times n$  matrix with  $m < n$ . In general, the solution of (1) is not unique. To recover  $x$  uniquely, some additional assumptions on  $x$  and  $A$  are necessary. We are concerned with the case that  $x$  is sparse. That is  $\|x\|_0 \ll n$ , where  $\|x\|_0$  is the number of nonzero entries of  $x$ . We say that a vector  $x$  is  $K$ -sparse when  $\|x\|_0 \leq K$ . The natural choice is seeking a sparse solution of the  $l_0$  problem

$$\min_x \|x\|_0, \quad s.t. \quad Ax = y \quad (2)$$

where  $A$  and  $y$  are known. To make sure the  $K$ -sparse solution is unique, we would like to use the *restricted isometry property* (RIP) which was introduced by Candès and Tao in [CT]. A matrix  $A$  satisfies the RIP of order  $K$  with *restricted isometry constant*  $\delta_K$  if  $\delta_K$  is the smallest constant such that

$$(1 - \delta_K)\|x\|_2^2 \leq \|Ax\|_2^2 \leq (1 + \delta_K)\|x\|_2^2 \quad (3)$$

holds for all  $K$ -sparse signal  $x$ . If  $\delta_{2K} < 1$ , the  $l_0$  problem has a unique  $K$ -sparse solution [C].

OMP is an effective greedy algorithm for seeking the solution of the  $l_0$  problem. Basic reference for this method in the signal processing literature are [DMA, PRK]. The iterative formula below supplies the framework of OMP.

**Input:**  $A, y$   
**Set:**  $\Omega_0 = \emptyset, r_0 = y, k = 1$ ;  
**while not converge**  
      $\circ \quad \Omega_k = \Omega_{k-1} \cup \arg \max_i |\langle r_{k-1}, A_i \rangle|$   
      $\circ \quad x_k = \arg \min_z \|A_{\Omega_k} z - y\|_2$   
          $\circ \quad r_k = y - A_{\Omega_k} x_k$   
      $\circ \quad k = k + 1$   
**end while**  
 $\hat{x}_{\Omega_k} = x_k, \hat{x}_{\Omega_k^c} = 0$

**Return**  $\hat{x}$ .

There are several natural stopping criteria for the OMP [T]. In this paper, we investigate conditions under which the OMP can reconstruct the  $K$ -sparse signals in  $K$  iteration successfully or not. There are several results on this subject. For example, Davenport and Wakin have proved that  $\delta_{K+1} < \frac{1}{3\sqrt{K}}$  is a sufficient condition for the successful reconstruction [DW]. Later, Liu and Temlyakov have improved the condition to  $\delta_{K+1} < \frac{1}{(1+\sqrt{2})\sqrt{K}}$  [LT]. An interesting open question raised by Liu and Temlyakov is: can we increase the constant  $1/(1+\sqrt{2})$  to 1? In contrast, Dai and Milenkovic conjectured that there exists a matrix satisfying the RIP of order  $K+1$  with  $\delta_{K+1} \leq 1/\sqrt{K}$  for which there exists a  $K$ -sparse signal  $x \in \mathbf{R}^n$  that cannot be

recovered exactly via  $K$  iterations of OMP [DM]. This conjecture has been confirmed via experiments in [DW] for the case  $K = 2$ . The contribution of this paper are twofold.

- Improve the sufficient condition for the successful recovered for OMP.  
If

$$\delta_{K+1} \leq \frac{1}{\sqrt{K} + 1},$$

then for all  $K$ -sparse  $x$ , Orthogonal Matching Pursuit will recover  $x$  exactly from  $y = Ax$  in  $K$  iterations.

- Give the positive answer to the conjecture in [DM]. For any given  $K \geq 2$ , we construct matrix with

$$\delta_{K+1} = \frac{1}{\sqrt{K}}$$

where OMP will fail for at least one  $K$ -sparse signal.

## 2 PRELIMINARIES

Before going further, we introduce some new notations. For the given  $K$ -sparse signal  $x$  and matrix  $A$ , we define

$$S_k := \langle A e_k, A x \rangle, \quad k = 1, \dots, n.$$

Denote  $S_0 := \max_{k \in \{1, \dots, K\}} |S_k|$ . The following lemma is useful in our analysis.

**Lemma 1.** *For the given  $K$ -sparse signal  $x$  with the support on  $\{1, \dots, K\}$ , if the restrict isometry constant  $\delta_{K+1}$  of a matrix  $A$  satisfies*

$$\delta_{K+1} < \frac{1}{\sqrt{K} + 1}, \quad (4)$$

then  $S_0 > |S_k|$  for  $k > K$ .

**Proof.** By Lemma 2.1 in [C], we have

$$|S_k| = |\langle A e_k, A x \rangle| \leq \delta_{K+1} \|x\|_2, \quad \forall k > K. \quad (5)$$

Furthermore, for the given  $K$ -sparse  $x$ , we have

$$\begin{aligned} \langle A x, A x \rangle &= \left\langle A \sum_{k=1}^K x_k e_k, A x \right\rangle \\ &= \sum_{k=1}^K x_k \langle A e_k, A x \rangle \\ &= \sum_{k=1}^K x_k S_k. \end{aligned}$$

From the definition of RIP, we have

$$\begin{aligned}
 (1 - \delta_{K+1})\|x\|_2^2 &\leq \langle Ax, Ax \rangle \\
 &= \sum_{k=1}^K x_k S_k \\
 &\leq S_0 \|x\|_1 \\
 &\leq S_0 \sqrt{K} \|x\|_2.
 \end{aligned}$$

This implies that

$$\frac{(1 - \delta_{K+1})\|x\|_2}{\sqrt{K}} \leq S_0. \quad (6)$$

Combining (5) and (6), we conclude that the lemma holds.  $\square$

### 3 Main Results

This section establishes the main result of this paper.

**Theorem 2.** *Suppose that  $A$  satisfies the RIP of order  $K$  with the restricted isometry constant*

$$\delta_{K+1} < \frac{1}{\sqrt{K} + 1}. \quad (7)$$

*Then for all  $K$ -sparse  $x$ , OMP can recover  $x$  exactly from  $y = Ax$  in  $K$  iterations.*

**Proof.** Without loss of generality, we assume that the support of the given signal  $x$  is  $\{1, 2, \dots, K\}$ . Now we can see that the sufficient condition for the OMP choosing the index in  $\{1, \dots, K\}$  at first step is

$$S_0 > |S_k|, \quad \forall k > K.$$

By Lemma 1, the first step of OMP is successful. Since the OMP make an orthogonal projection at each iteration, it can be proved by induction that the OMP chooses the right index at each step if (7) holds.  $\square$

**Theorem 3.** *For any given positive integer  $K \geq 2$ , there exist a  $K$ -sparse signal  $x$  and a matrix  $A$  with the restricted isometry constant*

$$\delta_{K+1} = \frac{1}{\sqrt{K}}$$

*for which OMP can fail in  $K$  iterations.*

**Proof.** For any given positive integer  $K \geq 2$ , let

$$x = (1, 1, \dots, 1, 0)^T \in \mathbf{R}^{K+1}.$$

Let

$$A = \begin{pmatrix} & & \frac{1}{K} \\ & I_K & \vdots \\ & & \frac{1}{K} \\ 0 & \dots & 0 & \sqrt{\frac{K-1}{K}} \end{pmatrix}_{(K+1) \times (K+1)}.$$

It is easy to see that the eigenvalues  $\{\lambda_k\}_{k=1}^{K+1}$  of  $A$  are

$$\lambda_k = 1, \quad k = 1, \dots, K-1,$$

and

$$\lambda_K = \sqrt{1 - \frac{1}{\sqrt{K}}}, \quad \lambda_{K+1} = \sqrt{1 + \frac{1}{\sqrt{K}}}.$$

Therefore, the restricted isometry constant  $\delta_{K+1}$  of  $A$  is equal to  $\frac{1}{\sqrt{K}}$ . By simple calculation, we have

$$A^T A = \begin{pmatrix} & & \frac{1}{K} \\ & I_K & \vdots \\ & & \frac{1}{K} \\ \frac{1}{K} & \dots & \frac{1}{K} & 1 \end{pmatrix}_{(K+1) \times (K+1)}.$$

It follows that

$$S_k = \langle A e_k, A x \rangle = \langle A^T A e_k, x \rangle = 1 \quad \forall k \in \{1, \dots, K+1\}.$$

This implies that the OMP can fail at first iteration. Since  $x$  is  $K$ -sparse, in each step, we can only choose one index. We conclude that the OMP can fail in  $K$  iterations for the given matrix  $A$  and  $x$ .  $\square$

**Remark 4.** *Achieving very small values for the restricted isometry constant is a challenging task. Theorem 3 shows the limitation of the OMP. Furthermore, if we select multiple columns per iteration, we can recover the  $K$ -sparse signal in  $K$  iterations. Actually, this technique has been widely used in many related greedy pursuit algorithms, such as CoSaMP [NT] and StOMP [DTDS].*

## Bibliography

- [C] E.J. Candès, The restricted isometry property and its implications for compressed sensing. *Compte Rendus de l'Academie des Sciences*, ser. I, 346:589-592, Paris.
- [CT] E.J. Candès and T. Tao, Decoding by linear programming. *IEEE Trans. Inf. Theory*, 51 4203-4215, 2005.
- [DM] W. Dai and O. Milenkovic, Subspace pursuit for compressive sensing signal reconstruction. *IEEE Trans. on Info. Theory*, 55(5) 2230-2249, 2009.

- [DMA] G. Davis, S. Mallat, and M. Avellaneda, Adaptive greedy approximation. *J. Constr. Approx.*, 13 57-98, 1997.
- [DW] M.A. Davenport and M.B. Wakin, Analysis of Orthogonal Matching Pursuit using the Restricted Isometry Property. *IEEE Trans. Inform. Theory*, 56(9) 4395-4401, 2010.
- [D] D. Donoho, Compressed sensing. *IEEE Trans. Inform. Theory*, 52(4) 1289-1306, 2006.
- [DTDS] D. L. Donoho, Y. Tsaig, I. Drori, and J.-L. Starck,  $\ell_1$  Sparse solution of underdetermined linear equations by stagewise Orthogonal Matching Pursuit (StOMP),  $\pm$  Stanford Univ., Palo Alto, Statistics Dept. Technical Report 2006-02, Mar. 2006.
- [LT] E. Liu and V.N. Temlyakov, Orthogonal Super Greedy Algorithm and Applications in Compressed Sensing, 2010.  
<http://dsp.rice.edu/sites/dsp.rice.edu/files/cs/LiuTemlyakov.pdf>
- [T] J. Tropp, Greed is good: Algorithmic results for sparse approximation. *IEEE Trans. on Info. Theory*, 50(10) 2231-2242, 2004.
- [NT] D. Needell and J. A. Tropp,  $\ell_1$ CoSaMP: Iterative signal recovery from incomplete and inaccurate samples,  $\pm$  *Appl. Comp. Harmonic Anal.*, 26(3) 301-321, 2009.
- [PRK] Y. C. Pati, R. Rezaifar, and P. S. Krishnaprasad, Orthogonal Matching Pursuit: Recursive function approximation with applications to wavelet decomposition. in *Proc. 27th Ann. Asilomar Conf. on Signals, Systems and Computers*, Nov. 1993.

[IEEEbiography|Qun Mo|](#)

received the Ph.D. degree in mathematics from the University of Alberta, Canada, in 2003. His research interests include wavelet analysis and its applications, wavelet frames and compressed

[IEEEbiography|Yi Shen|](#)

received the Ph.D. degree in mathematics from the Zhejiang University, China, in 2009. His research interests include wavelet analysis and its applications, wavelet frames and compressed